

For more information please click on part No.

Product	Product Info	Vin (Min) (V)	Vin (Max) (V)	Vout (Max) (V)	Isw (Typ) (A)	Iq (Typ) (mA)	Vfb (V)	Freq 1 (kHz)	Package 1	Package 2
<a href="#">MP3418</a>	400mA, 1.2MHz, Synchronous, Step-up Converter with Output Disconnect	0.6	4	4	0.4	0.038	1.21	1200	TSOT23-8	
<a href="#">MP3414</a>	1.8A, 1MHz, Synchronous, Step-up Converter with Output Disconnect	0.6	4	4	1.8	0.035	1.21	1000	TSOT23-8	
<a href="#">MP3120</a>	1.2A, 1.1MHz Synchronous Boost Converter with Output Disconnect	0.8	5	5	1.2	0.47	1.19	1100	TSOT23-6	
<a href="#">MP5410</a>	Low Start-up Voltage Boost Converter with Four SPDT Switches	1.8	5.5	10	0.18	0.028	1.23	Variable	QFN16	
<a href="#">MP5414</a>	PMU for 3D Glasses	1.8	5.5	10	0.18	0.028	1.23	Variable	QFN28	
<a href="#">MP3410</a>	1.3A, 550kHz Synchronous Rectified Step-up Converter	1.8	6	6	1.3	0.36	1.19	550	TSOT23-5	
<a href="#">MP3212</a>	1.3A, 1MHz Step-up Regulator with Integrated Input Disconnect Switch	2.3	5.5	28	1.3	0.18	1.23	1000	QFN10	-
<a href="#">MP3209</a>	1.4MHz, 350mA Boost Converter	2.5	6	22	0.35	0.64	1.25	1400	TSOT23-5	UTQFN8
<a href="#">MP3217</a>	36V, 670kHz Step-Up Converter with a 0.5A Switch	2.5	6	36	0.5	0.46	1.24	670	TSOT23-6	
<a href="#">MP3216</a>	36V, 1.3MHz, 0.75A Step-Up Converter With Output Disconnect	2.5	6	36	0.75	0.55	1.24	1300	TSOT23-6	
<a href="#">MP1541</a>	1.3MHz Boost Converter	2.5	6	22	1.9	0.635	1.25	1300	TSOT23-5	
<a href="#">MP1542</a>	700kHz/1.3MHz Boost Converter with 2A Switch	2.5	22	22	2.6	0.7	1.25	700/1300	MSOP8	
<a href="#">MP3213</a>	700kHz/1.3MHz Boost Converter with 3.5A Switch	2.5	22	22	3.5	0.7	1.25	700/1300	MSOP8E	
<a href="#">MP1517</a>	3A, 25V, 1.1MHz Step-Up Converter	2.6	25	25	4	0.9	0.7	1100	QFN16	
<a href="#">MP1531</a>	Low Power, Triple Output Step-Up Plus Charge Pump for TFT Bias	2.7	5.5	22	0.65	0.8	1.25	250	TSSOP16	QFN16
<a href="#">MP3430</a>	90V Step-Up Converter with APD Current Monitor	2.7	5.5	90	1.2	0.3	0.8	1300	QFN16	
<a href="#">MP1530</a>	Triple Output Step-Up Plus Linear Regulators for TFT Bias	2.7	5.5	22	3.6	1.3	1.25	1400	QFN16	TSSOP16
<a href="#">MP3425</a>	3A, 55V Boost Converter with Programmable Switching Frequency and UVLO	3.1	22	55	5	0.65	1.25	Variable	QFN14	
<a href="#">MP3426</a>	6A, 35V Boost Converter with Programmable Switching Frequency and UVLO	3.2	22	35	8.5	0.65	1.225	Programmable 300kHz to 2MHz	QFN14	-

For more information please click on part No.